



**AIRSTREAM DMX**

1226100318



**WiFLY NEI**

1226100296



**Specification**

- Creates wireless bridge between your Wifi device and ADJ lighting products equipped with WiFly or wired DMX512
- Allows you to use your iPhone or iPad as a lighting controller using the Airstream DMX app
- Compatible with all ADJ WiFLY and Elation Efly products
- Magnetic bottom plate for temporary, quick and easy mounting to metal fixtures or objects.
- Quick lock bracket included.
- Up to 2500 wireless feet (open line of sight) when using other "EXR Extended Range" WiFLY products
- One transmitter can send to many receivers using the same radio channel
- 14 WiFly Channels
- 3-pin DMX Out
- Wireless Frequency: 2.4 GHz DSSS
- Power Supply: DC 9-12V
- Dimensions (LxWxH): 5" x 7" x 2.5" / 125 x 175 x 62mm
- Weight: 1 lbs. / 0.5 kg.

**Features:**

- 432 Channel DMX Controller with ADJ's WiFLY Transceiver Wireless DMX on-board.
- Control up to 12 individual fixtures
- Designed for controlling moving lights and LED Pars of any brand that consist of 34 DMX channels or less
- Built-in effects generator for LED's and Moving Lights
- 12 Memories via 2 banks
- 4 Rotary Encoders for Channel & Function Control
- Master Dimmer Fader Control
- Strobe Rate Fader Control
- 6 Mode buttons (Fixture, Color, Gobo, Effect, Show, & Pause)
- 12 Multi-function buttons
- Blackout button
- Universal USB Port (USB Stick Included)

**Tech Specs:**

- DMX output connector: 3-pin XLR
- Power In: 9-12V DC min 300mA UL approved power supply (Included)
- Power consumption: 3.6 Watts
- Size: 12.8" x 7.25" x 2.75" (325 x 185 x 68.7mm)
- Weight: 4.4 lbs. (2 kgs.)