| Application | |
|---------------------------------------|--|
| Beam style | well-defined, flat field projection |
| Suitable for | theatres, TV studios, permanent shows, churches music bars |
| Specification level | and restaurants, sport-halls |
| Beam angle | professional range 8°- 22° Typical throw distance 4 – 20m |
| Electrical specifications | 5 22 Typical throw distance 4 25m |
| · · · · · · · · · · · · · · · · · · · | 20004150 00044 |
| Light source | 380W LED, RGBW |
| Supply Volts Fraguency / Current | 100/260V AC single phase |
| Frequency / Current Power consumption | 50/60Hz – 1.17A @ 230v ac- 2.35A @ 110V AC 250W at full power, 9W in sleep mode |
| USB PSU | integrated; allows re-charging of mobile device during operatio |
| Cable/connection | 2.2m, 3 x 1.5mm ² cable, Powercon to bare ends |
| Standards Compliance | EN60598-2-17, CE marked |
| Mechanical specification | |
| Lamp House Construction | extruded aluminium and sheet steel |
| Mounting | steel stirrup with 12mm centre hole and DIN mounting. spigot |
| | for ø29mm tube supplied |
| Pan & Tilt control | 2 side-handles head to rear |
| Weight/Packed weight | 21.0 kg / 26.0 kg |
| Operational specificatio | ns |
| Focus adjustment | slide zoom controls (diameter and softness) at side |
| DMX channels/connection | 6 or 7 ch/ XLR5 connectors, IN/OUT |
| RDM | integrated |
| WI-FI | integrated |
| Colour | RGBW |
| Colour control | by Android or IOS mobile device connected to proprietary Wi-F access point (1 device only – 12m) or remote DMX512-RDM |
| Dimming | positionable external activator Clamp-on dimmer, supplied or remote DMX 8 or 16 bits |
| LED temperature | built-in sensor for real time monitoring |
| Ambient temperature | 35°C max. |
| Fan speed control | 3 modes available Silent/Auto/Constant |
| Fade curves | 2 curves(linear, square) |
| LED Frequency | 16KHz – Flicker free |
| LCD display | set-up, DMX, monitor, diagnostics |
| Software upload | remote, via DMX 512 cables |
| Optical specifications | |
| Optical system | double condenser with variable zoom |
| LED array / rated life | RGBW, replaceable |
| Rated LED life | 50,000 hours at 25°C, maintains 70% of original intensity |
| Beam colour temperature | Any, from RGBW colour mixing |
| CRI (Colour Rendering Index) | >90 |
| Accessories | |
| Metal colour frame | ■20100106 Colour-changer 20105106 |
| Spare iris diaphragm | 20100707 Gobo holder A/B size 20100807 |
| Black tripod | 20102401 Chrome plated tripod 20102402 |
| Spare spigot ø29mm | 20102200 Spigot w/fluid head 20102100 |
| Flight case | 20107180 Remoto 20702072 |
| Clamp-on digital dimmer | 20702071 supplied |

| Accessories | | | |
|----------------------------------|---------------|----------------------|----------|
| Metal colour frame | 20100106 | Colour-changer | 20105106 |
| Spare iris diaphragm | 20100707 | Gobo holder A/B size | 20100807 |
| Black tripod | 20102401 | Chrome plated tripod | 20102402 |
| Spare spigot ø29mm | 20102200 | Spigot w/fluid head | 20102100 |
| Flight case | 20107180 | Remoto | 20702072 |
| Clamp-on digital dimmer | 20702071 | supplied | |
| Clamp-on universal phone holder | 20702073 | supplied | |
| Clamp-on Android mobile phone, p | re-loaded app | /colour library | 20702074 |

Photometric data


| Narrow bea | am(1/2 P | .A) | | | | | | | F | RGBW |
|---|------------------------------------|----------------------------|--------------------------|--------------------------|-------------------------|-------------------------|------|------|------|-------------------|
| Beam dia. | 0.3 | 0.5 | 0.7 | 0.9 | 1.0 | 1.2 | 1.4 | 1.6 | 1.7 | m |
| R | 12625 | 5 5611 | 3156 | 2020 | 1402 | 1030 | 789 | 623 | 505 | lux |
| G | 29875 | 1327 | 7 7468 | 4780 | 3319 | 2438 | 1867 | 1475 | 1195 | lux |
| В | 1375 | 611 | 343 | 220 | 152 | 112 | 85 | 67 | 55 | lux |
| W | 44000 | 19556 | 11000 | 7040 | 4889 | 3592 | 2750 | 2173 | 1760 | lux |
| Full | 40000 | 17778 | 10000 | 6400 | 4444 | 3265 | 2500 | 1975 | 1600 | lux |
| D:-t | | _ | • | _ | _ | 7 | 0 | ^ | 40 | |
| Distance | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | m |
| Wide beam Beam dia. | | | 1.6 | 1.9 | 2.3 | 2.7 | m | 9 | 10 | m |
| Wide beam | n(1/2 P.A | .) | | | | - | | 9 | 10 | lux |
| Wide beam Beam dia. | n (1/2 P.A 0.8 | .) | 1.6 | 1.9 | 2.3 | 2.7 | | 9 | 10 | |
| Wide beam Beam dia. R | 0.8 2625 | .) 1.2 1166 | 1.6 656 | 1.9 420 | 2.3 | 2.7 | | 9 | 10 | lux |
| Wide beam Beam dia. R G | 0.8 2625 6375 300 | 1.2 1166 2833 133 | 1.6 656 1594 | 1.9 420 1020 | 2.3 291 708 | 2.7 214 520 | | 9 | 10 | lux lux |
| Wide beam Beam dia. R G | 0.8 2625 6375 300 9625 | 1.2 1166 2833 133 | 1.6 656 1594 75 | 1.9 420 1020 48 | 2.3 291 708 33 | 2.7 214 520 24 | | 9 | 10 | lux lux lux |

astro 250 CM wi-fi

250W, 100/260VAC, DMX512 + RDM **RGBW** led followspot

part # ■ 01207190 Kit K01207190





Stylish, compact and extremely high efficiency RGBW led followspot with unique features allowing for precision and user-friendly control in any situation.

- Colour Control by Android or IOS mobile device connected to proprietary wi-fi access point (1 device only, 12m range) or remote DMX512-RDM
- USB port supplied to re-charge your mobile device while operating the followspot
- Clamp-on universal mobile phone holder, 3.5/6.5in, rotatable 360°, supplied
- Clamp on digital dimmer, positionable along the side bars to suit any operator's needs, supplied
- Android mobile phone, with pre-loaded proprietary colour library, on demand
- Free proprietary colour library available for download from our website for those using own mobile device

Standard delivery also includes iris diaphragm and spigot



Distribuito da: AMLUX SRL Via Belgio 11/13 46042 Castel Goffredo (MN), Italy tel: +39 0376 781094 info@amlux.it www.amlux.it