

1448 DC-4

CODE DM#0800208

Specifiche:

- 4 canali
- 42 Programmi
- Funzioni Dimmer, Sound-to-Light
- Programm-Speed, Auto Sound, Auto Speed, Fade Time
- Full-ON e Stand-by
- Audio input: 100 mV-Vp-p (6,3 Mono)
- DMX output: 3 poli XLR femmina

Features:

- 4 Channel
- 42 integrated chasing programs
- dimmer function, sound-to-light
- program speed, auto sound, auto speed, fade time
- full on and stand-by chaser speed
- audio input: 100mV-1Vp-p
- DMX output : 3pin XLR female

DATI TECNICI	TECHNICAL DATA
Dimensioni (LxAxP) 483 x 45 x 132 mm	Dimensions (LxHxB) 483 x 45 x 132mm
Peso 1,35 kg	Weight 1,35 kg

AC 230 V
50 Hz

Connector
DMX
OUT

Sound
to
light



1470 DC-8

CODE CE#0800201

Specifiche:

- 8 canali
- 48 Programmi
- Funzioni Dimmer, Sound-to-Light
- Programm-Speed, Auto Sound, Auto Speed, Fade Time
- Full-ON & Stand-by
- Audio input: 100 mV-Vp-p (6,3 Mono)
- DMX output: 3 poli XLR femmina

Features:

- 8 Channel
- 48 integrated chasing programs
- dimmer function, sound-to-light
- program speed, auto sound, auto speed, fade time
- audio input: 100mV
- full on and stand-by chaser speed
- DMX output : 3pin XLR female

DATI TECNICI	TECHNICAL DATA
Dimensioni (LxAxP) 483 x 45 x 132 mm	Dimensions (LxHxB) 483 x 45 x 132mm
Peso 1,55 kg	Weight 1,55 kg

AC 230 V
50 Hz

Connector
DMX
OUT

Sound
to
light



1471 DC-12

CODE DM#1200201

Specifiche:

- 12 canali
- 53 Programmi
- Funzioni dimmer, Sound-to-Light
- Programm-Speed, Auto Sound, Auto Speed, Fade Time
- Full-ON e Stand-by
- Audio input: 100 mV-Vp-p (6,3 Mono)
- DMX output: 3polil XLR femmina

Features:

- 12 Channel
- 53 integrated chasing programs
- dimmer function, sound-to-light
- program speed, auto sound, auto speed, fade time
- full on and stand-by chase speed
- audio input: 100mV
- DMX output : 3pin XLR female

DATI TECNICI	TECHNICAL DATAS
Dimensioni (LxAxP) 483 x 45 x 132 mm	Dimensions (LxHxB) 483 x 45 x 132mm
Peso 1,5 kg	Weight 1,5 kg

AC 230 V
50 Hz

Connector
DMX
OUT

Sound
to
light

